







Traxxas Exclusive! Integrated Balance Connector

The balance wires are integrated into the main connector for fast, easy, and rugged connection to Traxxas LiPo chargers. Fragile balance wires, balance boards, and tiny connectors are eliminated.

A Traxxas LiPo charger or adapter compatible with the integrated balance connector is required for charging this battery.



Specifications:

Configuration: 4s1p Continuous Discharge: 25C (168A) Max Burst Rate: 50C (336A) Watt Hours: 99.16 Charge Rate: 1C (6.7A) Max Charge Rate: 3C (20.1A) Dimensions (mm): 178x44x50.5 Weight: 22.7oz (644g)



4S





WARNING! CAUTION! DANGER!

FIRE HAZARD! Read and follow manufacturer's charging and handling instructions, warnings and precautions before use! LiPo Batteries pose a severe risk of fire if not properly handled and charged per the instructions. Never allow children under 14 years old to charge batteries without the supervision of a responsible, knowledgeable adult

- While charging, always place the battery in a fire retardant/fire proof container and on a non-flammable surface such as concrete.
- ALWAYS charge batteries in a well-ventilated area.
- REMOVE flammable items and combustible materials from the charging area.

 • Use ONLY a Traxxas iD equipped LiPo charger with this battery.
- DO NOT charge with a NiMh only charger.

- If any battery or cell is damaged in any way, do NOT charge, discharge, or use the battery.
- ALWAYS confirm charger settings match this battery prior to charging.
 Do NOT exceed the maximum recommended charge rate.
- Do NOT disassemble, crush, short circuit or expose to flame.
- NEVER leave batteries unattended during charging.





Use with Traxxas iD Chargers for the easiest and safest charging solution Traxxas® iD™ chargers auto-detect iD equipped Traxxas batteries and automatically optimize charge settings for worry-free charging*





