

Model	Ports	PWM Outputs	S.Bus Ports	S.Bus2 Ports	Channel Mode Settings	FASST	Telemetry	S-FHSS	High Speed	HV	Connector	Range
R2004GF	5	4	0	0	No	No	No	FHSS	No	Yes	J (STND)	Parkflyer
R2006GS	7	6	0	0	No	No	No	Yes	Yes	Yes	J (STND)	Full-range
R2008SB	8	8	1	0	No	No	No	Yes	Yes	Yes	J (STND)	Full-range
R2106GF	6	6	0	0	No	No	No	Yes	Yes	Yes	J (STND)	Parkflyer
R2001SB	2	1	1	0	No	No	No	Yes	Yes	Yes	J (STND)	Full-range
R3001SB	2	1	1	1	Yes - S.Bus, 3 Ch.	No	Yes (T-FHSS)	No	Yes	Yes	J (STND)	Full-range
R3004SB	5	4	0	1	No	No	Yes (T-FHSS)	No	Yes	Yes	J (STND)	Full-range
R3006SB	7	6	1	1	Yes - S.Bus, 6 Ch.	No	Yes (T-FHSS)	No	Yes	Yes	J (STND)	Full-range
R3106GF	7	6	0	0	No	No	No	No	No	Yes	J (STND)	Full-range
R3008SB	9	8	1	1	Yes - 4 Modes	No	Yes (T-FHSS)	No	Yes	Yes	J (STND)	Full-range
R6004FF	6	4	0	0	No	Yes	No	No	No	No	J (STND)	Indoor
R6008HS	9	8	0	0	Yes - Hi-Speed/Normal	Yes	No	No	Yes	No	J (STND)	Full-range
R6014HS	16	14	0	0	Yes - Hi-Speed/Normal	Yes	No	No	Yes	No	J (STND)	Full-range
R6106HF	6	6	0	0	Yes - Hi-Speed/Normal	Yes	No	No	Yes	Yes	J (STND)	Parkflyer
R6106HFC	6	6	0	0	Yes - Hi-Speed/Normal	Yes	No	No	No	Yes	J (STND)	Mid-range
R616FFM	7	6	0	0	No	Yes	No	No	No	No	Micro	Indoor or Parkflyer
R617FS	7	7	0	0	No	Yes	No	No	No	No	J (STND)	Full-range
R6202SBW	4	2	2	0	Yes - Hi-Speed/Normal	Yes	No	No	Yes	Yes	J (STND)	Full-range
R6203SB	4	3	1	0	Yes - Hi-Speed/Normal	Yes	No	No	Yes	Yes	J (STND)	Full-range
R6203SBE	4	3	1	0	Yes - Hi-Speed/Normal	Yes	No	No	Yes	Yes	J (STND)	Parkflyer
R6208SB	9	8	1	0	Yes - Hi-Speed/Normal	Yes	No	No	Yes	Yes	J (STND)	Full-range
R6303SB	4	3	1	0	Yes - Hi-Speed/Normal, 7 Modes	Yes	No	No	Yes	Yes	J (STND)	Full-range
R6303SBE	4	3	1	0	Yes - Hi-Speed/Normal, 7 Modes	Yes	No	No	No	No	J (STND)	Parkflyer
R7003SB	4	3	1 to 2	1	Yes - 11 Modes	No	Yes (FASSTest)	No	Yes	Yes	J (STND)	Full-range
R7008SB	9	8	1	1	Yes - 4 Modes	No	Yes (FASSTest)	No	Yes	Yes	J (STND)	Full-range
R7006SB	6	6	1	1	Yes - 4 Modes	No	Yes (FASSTest)	No	Yes	Yes	J (STND)	Full-range
R7018SB	21	18	1	1	Yes - FASSTest/FASST Multi, Hi-Speed/Normal	No	Yes (FASSTest)	No	Yes	Yes	J (STND)	Full-range

